

Waybler Adapt

Waybler

The charger must only be used for EV charging and engine block heating with an approved adapter.
All external equipment must be checked before use to ensure they are not damaged.

Charging

Charging current	6-32 A
Charging output	1,4-22 kW*
Charging socket	Type 2
Charging method	Mode 3
Nr. of charging sockets	1 socket
Phases	3-phase, active phase selection
Energy measurement	MID approved
Earth fault detection	Integrated earth fault detection, 30mA AC, 6mA DC Semi-automatic
Earth fault reset	Yes
Locking motor	Yes
Charging standard	IEC 61851-1 and EN 62196-2

Electrical connection

Electrical connection	16mm ² terminal block
Electrical grid Voltage	TN network
Frequency	230 V/400 V
Phases	50 Hz
	1-phase or 3-phase

Communications

Communications protocols	WCP, OCPP 1.6 (2.0.1 to come) Hardware prepared for ISO 15118 from 01/01/2027
Connections	Wifi, Ethernet, LTE (Option)
Modbus	Yes (Option)
Energy meter	Visible MID

Connection & Enclosure

Material	Aluminium
Enclosure class	IP 54
Impact resistance	IK10
Operating temperature	-30 °C to +50 °C
Placement	Wall bracket 60mm pipe bracket for single box 60mm pipe bracket for double mounting Triangular key 10
Enclosure lock	IEC 61439-7
Standard	5,1 kg
Weight	262 mm x 335mm x 140mm excl. charging socket
Dimensions	288mm x 335mm x 140mm incl. charging socket

User interface

Authentication	App, RFID (Option)
Status	LED (RGB)*

*If the indicator light on the charger shows red, remove the cable. If it still shows red, do not use the charger and contact support.

*Delivered power output may be affected by the available capacity of the electrical installation, load balancing, and the ambient temperature as well as the temperature inside the charger.

Hereby, Waybler AB declares that the radio equipment type Adapt, is in compliance with RED directive (2014/53/EU). The full text of the EU declaration of conformity is available at the following Internet address: <https://waybler.com/en/regulatory-2/>

